



Model	Part Number Terminal Leadwire	Bearing System	Rated Voltage	Freq.	Current	Input Power	Speed	Air Flow	Static Pressure	Noise Level	Weight
(型号)	(端子/出线)	(轴承)	(V)	(Hz)	(A)	(W)	(RPM)	(CFM)	(Inch-H ₂ O)	(dB-A)	(g)
			(电压)	(频率)	(电流)	(功率)	(转速)	(风量)	(静压)	(噪音值)	(重量)
SJ2206HA1	2206HA1BAT(L)	Ball	110/120	50/60	0.35/0.42	37/49	2800/3200	400/450	0.28/0.36	61/66	1430
SJ2206HA2	2206HA2BAT(L)	Ball	220/240	50/60	0.17/0.21	38/51	2800/3200	400/450	0.28/0.36	61/66	1430